

# GAMMA PHITS GPH-K23X

for Kenwood SP23\*



## Specifications

Cone:.....	Polypropylene IP64
Power:.....	10 W
Impedance:.....	8 Ohms
Frequency Response:.....	80-20000 Hz
Sensitivity:.....	83 dB
Weight:.....	240 g

# GAMMA PHITS GPH-K23X

## Assembly

1. Remove the top cover and the front panel.
2. Remove the driver together with its support unscrewing the four screws.
3. Unsolder red (+) and black (-) cables.



Photo 1

4. Take off the protector and stick the foams like it shows on photo 1.
4. Place the adapter ring in the place of the driver.
5. Place the new driver GPH-K23 on the top of the adapter ring and solder the cables again.

6. Use the cylinder spacer and the screws supplied to fix the driver with the flanges (photo 2) and solder the cables again.



Photo 2

7. Replace both front panel and top cover.